# EAX<sup>®</sup> SERIES EAX-2500

## AC/DC External Powered Wall Mount Exit Alarm

The Detex EAX-2500 Series Exit Alarm is designed for applications requiring a hardwired AC/DC alarm on secure doors. The alarm, with approximately 100dB, will sound when an unauthorized exit occurs. The smaller size of the EAX-2500, which is designed to fit in a standard 4"x4" outlet box, makes it the choice for quick and easy installations on emergency exit and restricted doors.



Specify EAX-2500SxMC65



Specify EAX-2500SxBKxMC65

### **Benefits**

Dellellts		
<ul> <li>Field selectable features allow customer to choose status indicators and auto rearm options</li> </ul>	<ul> <li>Easy to install using ordinary tools to save time and money</li> </ul>	<ul> <li>Available in either gray or black to blend with any décor</li> </ul>
100dB piezo horn provides security for restricted doors	<ul> <li>New graphics on cover are easy to understand and make key operation simple</li> </ul>	
Features		
Surface and flush mount available using 4"x4" double switch/outlet box	<ul> <li>AC/DC hardwired power with optional 9VDC backup battery</li> </ul>	<ul> <li>Tamper resistant housing and cover protects electronics</li> </ul>
<ul> <li>Patented cam assembly automatically adjusts for different size cylinders without spacers</li> </ul>	<ul> <li>Low battery alert is field selectable</li> </ul>	<ul> <li>Extended bypass allows alarm to remain silenced when door is open and automatically rearm upon closing of door</li> </ul>
	<ul> <li>Silent arming feature is field selectable</li> </ul>	
<ul> <li>Inside Key Control uses mortise cylinder with standard Yale cam</li> </ul>		<ul> <li>Relay output for signaling externa accessories</li> </ul>
Mechanical Options		
<ul> <li>KS - Key Stop (Key removed only when armed)</li> </ul>	• EAX-2500FK1 - Complete kit contains alarm, warning sign, flush back box, flush magnetic switch and 24VAC transformer (add suffix "xMC65 or xIC7" to include factory installed cylinder)	• EAX-2500SK1 - Complete kit contains alarm, warning sign, surface back box, surface magnetic switch and 24VAC transformer (add suffix "xMC65 or xIC7" to include factory installed cylinder)
EAX-2500 Flush or Surface		



### **Other EAX Exit Alarms Include**

- EAX-500 Battery Powered
- EAX-500W Weatherized **Battery Powered**

#### Accessories

- IC7 Interchangeable mortise cylinder (can be factory installed)
- MC65 Mortise cylinder (can be factory installed)

• EAX-3500 - Timed Bypass and

Rechargeable Battery

• MS-2049, MS-1039, MS-1059 -Magnetic Switch

- EAX-300 Door Prop
- EAX-300W Weatherized Door Prop
- Optional Cylinder Nut Wrench P/N: 103779


**Detex Limited Warranty** 


3 Year Limited Manufacturers


Warranty

#### **Dimensions**


#### Front and Side View







Surface mounting



Flush mounting

Door switch actuated Double door application as shown above available with EAX-500, EAX-300, EAX-2500 and EAX-3500. Note: Double door application as shown above not available with EAX-300W or EAX-500W weatherized alarms.



**Detex Corporation** 302 Detex Drive New Braunfels, Texas 78130-3045 USA PH. (830) 629-2900 (800) 729-3839 FAX (830) 620-6711 (800) 653-3839 http://www.detex.com USA Sales: marketing@detex.com International Sales: export@detex.com

3.11

4 00